



► PSEN op4B/1 Series

PILZ
THE SPIRIT OF SAFETY

Operating Manual-1003356-EN-04
- PSEN sensor technology



This document is the original document.

Where unavoidable, for reasons of readability, the masculine form has been selected when formulating this document. We do assure you that all persons are regarded without discrimination and on an equal basis.

All rights to this documentation are reserved by Pilz GmbH & Co. KG. Copies may be made for the user's internal purposes. Suggestions and comments for improving this documentation will be gratefully received.

Pilz®, PIT®, PMI®, PNOZ®, Primo®, PSEN®, PSS®, PVIS®, SafetyBUS p®, SafetyEYE®, SafetyNET p®, the spirit of safety® are registered and protected trademarks of Pilz GmbH & Co. KG in some countries.



SD means Secure Digital

1	Introduction	6
1.1	Validity of documentation	6
1.2	Using the documentation	6
1.3	Definition of symbols	6
2	Overview	8
2.1	Product types	8
2.2	Unit features	9
2.3	Types	10
2.3.1	Safety light grid without integrated muting sensors	10
2.3.2	Safety light grid with integrated muting sensors	11
2.4	Scope	14
3	Safety	15
3.1	Intended use	15
3.2	Safety regulations	16
3.2.1	Safety assessment	16
3.2.2	Use of qualified personnel	16
3.2.3	Warranty and liability	16
3.2.4	Disposal	16
4	Function description	17
4.1	Basic function	17
4.1.1	Function settings when delivered	18
4.2	Restart after safety light grid is activated	19
4.3	Reset function	20
4.4	EDM	21
4.5	Muting	22
4.5.1	Technical implementation	24
4.5.2	Time monitoring - Timeout	27
4.6	Override	28
4.7	Test function	30
4.8	Convert type without muting sensors to L/T-type	30
5	Project configuration	31
5.1	Maintaining the safety distance	31
5.2	Ambient conditions	31
5.3	Distance from reflective surfaces	32
5.4	Installation of several adjacent safety light grids	33
5.5	Use of deviating mirrors	35
5.6	Use of the muting function	36
6	Installation and wiring	41
6.1	Attach safety light grid without muting sensors to mounting surface	41
6.2	Attach safety light grid with muting sensors to mounting surface	41
6.3	Conversion of safety light grids without muting sensors	42
6.4	Installation of external muting sensors	43
6.5	Wiring	44

6.5.1	General guidelines	44
6.5.2	Connector pin assignment	44
6.5.3	TEST/START button	46
6.5.4	EDM	46
6.5.5	Earthing the safety light grid	47
6.5.6	Connections for muting	47
6.5.7	Wiring of external sensors on the safety light grid	48
7	Commissioning	49
7.1	Setting the functions	49
7.1.1	Open DIP switch cover	49
7.1.2	Activate muting	49
7.1.3	Set muting timeout	50
7.1.4	Activate EDM	50
7.1.5	Restart after unit is triggered	51
7.2	Orientation	51
7.2.1	General guidelines	51
7.2.2	Safety light grid alignment	52
7.2.3	Muting sensor alignment	53
7.2.4	LED support during alignment	54
7.3	Checking the safety light grid	54
7.4	System connection	55
8	Operation	56
8.1	Status information during operation	56
8.2	Perform test	57
8.3	Diagnostics and troubleshooting	57
8.3.1	Indicators for fault diagnostics	57
8.3.2	Perform reset	59
9	Regular checks and maintenance	60
9.1	Checks	60
9.1.1	Regular checks	60
9.1.2	Daily check	60
9.1.3	Check after plant/machine modification	60
9.2	Maintenance	61
10	Dimensions	62
11	Technical details	64
11.1	Safety characteristic data	70
12	Order reference	71
12.1	Order reference for safety light grids	71
12.2	Order reference for accessories	71
13	Appendix	74
13.1	Check list	74

14 EC declaration of conformity77

1 Introduction

1.1 Validity of documentation

This documentation is valid for the product PSEN op4B/1 Series. It is valid until new documentation is published.

This operating manual explains the function and operation, describes the installation and provides guidelines on how to connect the product.

1.2 Using the documentation

This document is intended for instruction. Only install and commission the product if you have read and understood this document. The document should be retained for future reference.

1.3 Definition of symbols

Information that is particularly important is identified as follows:



DANGER!

This warning must be heeded! It warns of a hazardous situation that poses an immediate threat of serious injury and death and indicates preventive measures that can be taken.



WARNING!

This warning must be heeded! It warns of a hazardous situation that could lead to serious injury and death and indicates preventive measures that can be taken.



CAUTION!

This refers to a hazard that can lead to a less serious or minor injury plus material damage, and also provides information on preventive measures that can be taken.



NOTICE

This describes a situation in which the product or devices could be damaged and also provides information on preventive measures that can be taken. It also highlights areas within the text that are of particular importance.



INFORMATION

This gives advice on applications and provides information on special features.

2 Overview

2.1 Product types

Product type	Protected field	
	Max. height in mm	Max. width in m
PSEN op4B-2-050/1	515	50
PSEN op4B-3-080/1	815	50
PSEN op4B-4-090/1	915	50
PSEN op4B-4-120/1	1215	50

Table of product types – Safety light grid without integrated muting sensors

Product type	Protected field	
	Max. height in mm	Max. width in m
PSEN op4B-L-050/1		
▶ Safety light grid	515	50
▶ Muting sensor		3
PSEN op4B-L-080/1		
▶ Safety light grid	815	50
▶ Muting sensor		3

Table of product types – Safety light grid with L-muting

Product type	Protected field	
	Max. height in mm	Max. width in m
PSEN op4B-T-050/1		
▶ Safety light grid	515	50
▶ Muting sensor		3
PSEN op4B-T-080/1		
▶ Safety light grid	815	50
▶ Muting sensor		3

Table of product types – Safety light grid with T-muting

Height

The height of the protected field describes the effective protected height, in which a matt, opaque object corresponding to the specific resolution will be detected.

Width

The maximum width of the protected field is determined by the maximum operating range of the light beam sent from the transmitter to the receiver.

In the table of product types, the maximum width for types with integrated muting sensors is divided into a maximum width for the safety light grid and a maximum width for the muting sensors.

- ▶ If the safety light grid is used without muting sensors, the width stated for the safety light grid will apply.
- ▶ If the safety light grid is used with muting sensors, the width stated for the muting sensors will apply.

The minimum width of the protected field corresponds to the minimum operating range stated in the [Technical details](#)  64].

2.2

Unit features

Safety light grids in the PSEN op4B/1 Series are multibeam optoelectronic protective devices for work areas in which

- ▶ machines,
- ▶ robots and
- ▶ automated plants

could endanger the physical integrity of operators.

Features of the safety light grid

- ▶ Type 4
- ▶ Safeguards protected fields with body resolution
- ▶ Muting

All safety light grids in the PSEN op4B/1 Series are able to process data from connected muting sensors

- ▶ Infrared protected field is generated
- ▶ Transmitter and receiver are synchronised optically
- ▶ Override
- ▶ LED for status information
- ▶ LED for support during alignment

2.3 Types

2.3.1 Safety light grid without integrated muting sensors

► Safety light grid with body resolution

The safety light grid is equipped for muting applications. External muting sensors with reflective sensors or with transmitter and receiver sensors can be used for muting applications (see [Order reference for accessories, section on muting accessories](#) [73]).





Fig.: View of safety light grid without integrated muting sensors

Legend

- [1] Receiver
- [2] Transmitter
- [3] LED on receiver/transmitter
- [4] Height of the protected field
- [5] Width of the protected field
- [6] 8-pin and 5-pin connector of receiver
- [7] 4-pin and 5-pin connector of transmitter

2.3.2 Safety light grid with integrated muting sensors



- [1] Receiver
- [2] Transmitter
- [3] LED on receiver/transmitter
- [4] Width of the protected field
- [5] Height of the protected field
- [6] 8-pin and 5-pin connector of receiver
- [7] 4-pin and 5-pin connector of transmitter
- [8] Muting sensors
- [9] 4-pin connector of muting sensors for connection to receiver/transmitter

L-muting application

Use L-type with muting sensors in one direction when material is moved through the danger zone from one direction

- ▶ PSEN op4B-L-050/1
- ▶ PSEN op4B-L-080/1




Fig.: L-type muting in one direction (integrated muting sensors)

Legend

- A1 Position of the first light beam on the muting sensor
- B1 Position of the second light beam on the muting sensor

T-muting application

Use T-types with muting sensors in two directions when material is moved through the danger zone from two directions

- ▶ PSEN op4B-T-050/1
- ▶ PSEN op4B-T-080/1




Fig.: T-type muting in two directions (integrated muting sensors) - View of the travel direction from right to left

Legend

- A1 Position of the first light beam on the muting sensor
- B1 Position of the second light beam on the muting sensor
- A2 Position of the third light beam on the muting sensor
- B2 Position of the fourth light beam on the muting sensor

2.4 Scope

Safety light grid with body resolution, without integrated muting sensors

Order reference	Description
PSEN op4B-2-050/1 or PSEN op4B-3-080/1 or PSEN op4B-4-090/1 or PSEN op4B-4-120/1	Safety light grid, consisting of ▶ Transmitter ▶ Receiver ▶ Mounting kit

Safety light grid with body resolution and integrated muting sensors (for muting in one direction)

Order reference	Description
PSEN op4B-L-050/1 or PSEN op4B-L-080/1	Safety light grid, consisting of ▶ Transmitter ▶ Receiver ▶ Mounting kit ▶ 2 integrated muting sensors ▶ Cable for connecting the muting sensors ▶ Mounting kit for muting sensors

Safety light grid with body resolution and integrated muting sensors (for muting in two directions)

Order reference	Description
PSEN op4B-T-050/1 or PSEN op4B-T-080/1	Safety light grid, consisting of ▶ Transmitter ▶ Receiver ▶ Mounting kit ▶ 4 integrated muting sensors ▶ Cable for connecting the muting sensors ▶ Mounting kit for muting sensors

3 Safety

3.1 Intended use

Safety light curtains in the PSEN op4B/1 Series constitute electrosensitive protective equipment. They are used to protect personnel and systems. The safety light curtains are designed to

- ▶ Safeguards protected fields with body resolution
- ▶ Safeguard danger zones and
- ▶ Safeguard access.

The safety light curtain may only be used for personal protection on machinery if

- ▶ The hazardous state can be stopped by the safety light curtain and/or
- ▶ The machine can be prevented from starting up.

Ensure that the start-up method meets the defined safety requirements.

- ▶ Without restart interlock (status when delivered) or
- ▶ With restart interlock

Intended use includes making the electrical installation EMC-compliant.

The product is designed for use in an industrial environment. Interference may occur if used within a domestic environment.

Before using the safety light grid, check whether the safety light grid's housing material can withstand the chemical substances used in the production process (see [Technical details](#)  64).

Serial numbers on transmitters and receivers

- ▶ Transmitters and receivers should only be installed, operated and replaced in pairs.
- ▶ Transmitters and receivers have the same serial number.

Repair information:

- ▶ Please always send transmitters and receivers with the same serial number for repair.
(During the repair, both units will be programmed to the current software status.)

The following is deemed improper use:

- ▶ Using the safety light curtains outdoors
- ▶ Using the safety light curtains to protect against flying parts
- ▶ Using the safety light curtains in a radioactive environment
- ▶ Using the safety light curtains outside the areas described in this manual
- ▶ Using the safety light curtains outside the documented [Technical Details](#)  64].



INFORMATION

Other safety devices and protective measures may be required in addition to the safety light curtain. These should be determined via a safety assessment based on the specific application range and specific local conditions (e.g. official specifications).

3.2 Safety regulations

3.2.1 Safety assessment

Before using a device, a safety assessment in accordance with the Machinery Directive is required.

The product as an individual component fulfils the functional safety requirements in accordance with EN ISO 13849 and EN IEC 62061. However, this does not guarantee the functional safety of the overall plant/machine. To achieve the relevant safety level of the overall plant/machine's required safety functions, each safety function needs to be considered separately.

3.2.2 Use of qualified personnel

The products may only be assembled, installed, programmed, commissioned, operated, de-commissioned and maintained by persons who are competent to do so.

A competent person is a qualified and knowledgeable person who, because of their training, experience and current professional activity, has the specialist knowledge required. In order to inspect, assess and handle products, devices, systems, plant and machinery, this person must be familiar with the state of the art and the applicable national, European and international laws, directives and standards.

It is the company's responsibility only to employ personnel who

- ▶ Are familiar with the basic regulations concerning health and safety / accident prevention,
- ▶ Have read and understood the information provided in the section entitled Safety
- ▶ Have a good knowledge of the generic and specialist standards applicable to the specific application.

3.2.3 Warranty and liability

All claims to warranty and liability will be rendered invalid if

- ▶ The product was used contrary to the purpose for which it is intended,
- ▶ Damage can be attributed to not having followed the guidelines in the manual,
- ▶ Operating personnel are not suitably qualified,
- ▶ Any type of modification has been made (e.g. exchanging components on the PCB boards, soldering work etc.).

3.2.4 Disposal

- ▶ In safety-related applications, please comply with the mission time T_M in the safety-related characteristic data.
- ▶ When decommissioning, please comply with local regulations regarding the disposal of electronic devices (e.g. Electrical and Electronic Equipment Act).

4 Function description

4.1 Basic function

The safety light grid consists of a transmitter and receiver, which are housed in rugged aluminium profiles and therefore protected from external damage.

The protected area is covered by infrared light beams, which are emitted from the transmitter to the receiver. The protected field that is produced is able to detect an opaque object.

As soon as an object or part of the operator's body interrupts the beams sent by the transmitter, the output signal switching device (OSSD) is immediately switched off and the connected machine is stopped immediately as a result. The object or body part must be at least the size of the resolution covered by the safety light grid.

The functions of the safety light grid are set via DIP switches, which are located beneath a flap on the connector side of the safety light grid. The electrical connection is made via an M12 connector, which is positioned underneath the profiles.

The following functions are set via DIP switches:

- ▶ Timeout muting
- ▶ Muting
- ▶ EDM
- ▶ Restart after unit is triggered

The transmitter and receiver are synchronised optically, so the two units do not have to be connected directly to each other.

The infrared beams that are transmitted and received are controlled and monitored via microprocessors, which provide the user with information about the operating state of the safety light grid and the potential error state via LED indicators. During the installation phase, two yellow LEDs simplify the alignment of the two units.

The indicators are described under:

- ▶ [Status information during operation](#) [ 56],
- ▶ [LED support during alignment](#) [ 54],
- ▶ [Indicators for fault diagnostics](#) [ 57].

4.1.1 Function settings when delivered

The safety light grid is delivered with all DIP switches in the ON position.




Fig.: DIP switches all ON

As a result the functions are set as follows:

Function	DIP switch	Position	Set function
Timeout muting	1 and 5	ON	10 minutes
Muting	2 and 6	ON	T-configuration (4 beams) or cross muting When using the L-configuration, DIP switches 2 and 6 must be set to OFF.
EDM	3 and 7	ON	Deactivated
Restart interlock	4 and 8	ON	Without restart interlock

Functions can be selected via DIP switch - settings when delivered

4.2 Restart after safety light grid is activated

If the safety light grid has switched off the OSSDs, the connected machine is stopped.

Once the protected field is clear again, the safety light grid must be reset to its normal operating state.

The restart can be achieved in two ways:

► Without restart interlock (status when delivered)

The safety light grid is automatically reset to its normal operating state.

► With restart interlock

The light grid is not reset to its normal operating state until

- The TEST/START button has been operated for at least 0.5 s and
- The area of the protected field is clear again and the light beams are no longer interrupted.



NOTICE

The machine may only be restarted via a TEST/START button.

It must not be possible to operate the pushbutton from inside the danger zone. The button must be located at a position from which there is a full, unobstructed view of the danger zone.




Fig.: Timing diagram for restart in operating mode with restart interlock

The type of restart that will be used is set during commissioning via DIP switches 4 and 8 (see [Setting the functions](#) [49]).

4.3 Reset function

In the event of an internal error on the safety light grid, the safety light grid switches to a safe condition and stops the connected machine. In order to restore normal operating conditions, the safety light grid must be reset.

Internal errors are:

- ▶ Malfunction of the outputs or
- ▶ Optical malfunction or
- ▶ Malfunction of the muting display or
- ▶ Incorrect operation of the EDM function.




Fig.: Timing diagram - Reset after malfunction

4.4 EDM

Contactors outside the safety light grid can be monitored (External Device Monitoring = EDM, also known as feedback loop monitoring).

EDM only needs to be activated if the contactors are controlled directly.

A test is performed to see that the N/C contacts switch if the state of the OSSD changes and so is used to monitor and detect malfunctions on the contactors. If a malfunction is detected, the safety light grid switches to a safe condition and stops the connected machine. This check is carried out each time the OSSD is triggered and before restarting.




Fig.: Timing diagram EDM

$T_c \geq 350 \text{ ms}$	After the OSSD outputs are switched on, the EDM circuit must open within 350ms
$T_0 \geq 100 \text{ ms}$	After the OSSD outputs are switched off, the EDM circuit must close within 100ms

Use control elements whose dynamics match the times stated at T_c and T_0 .

The function is controlled via DIP switches 3 and 7 (see [Setting the functions](#)  49).

4.5 Muting

The muting function can be used to suspend the safety light curtain during operation, subject to special operating conditions.

► Example of a special operating condition:

- Material is transported into the protected field on a conveyor and the safety light curtain is overridden for the time it takes the material to pass through

Muting proves to be particularly suitable when, under certain operating conditions, an object is permitted to pass through the danger zone but a person is not.

The following diagrams illustrate application examples for the three product types.




Fig.: L-type muting in one direction (integrated muting sensors)




Fig.: T-type muting in two directions (integrated muting sensors)




Fig.: Muting in two directions with type without muting set and external muting sensors



CAUTION!

Risk of injury due to loss of the safety function

In muting status, the OSSDs continue to be in ON state. The connected machine remains in operation and represents a potential hazard.

- Prevent the possibility of access to the danger zone during muting.

Identification of the conveyed material (pallets, vehicles...) must be guaranteed with all

- ▶ Material dimensions and
- ▶ Conveyor speeds

that are intended to arise during operation.

4.5.1 Technical implementation

The safety light grid has two inputs, Muting 1 and Muting 2, to activate the muting function.

The muting sensors are connected to these inputs. The muting sensors must be positioned and installed at a right angle to the receiver and transmitter (see [Installation and wiring](#) [ 41]).

- ▶ The muting status occurs
 - when the first sensor and the second sensor detect a conveyed material simultaneously or
 - when the first sensor has detected a conveyed material and the second sensor also detects it max. 4 s afterwards.



CAUTION!

Transport speed too low

If the transport speed is too low, the muting state is not triggered by passing material.

Select the transport speed so that the passing material passes both sensors within max. 4 s.



CAUTION!

Ending the muting status

Use a mechanical barrier (see diagram) to prevent access to the danger zone once muting is ended.




Fig.: Application for muting in one direction - Danger zone is safeguarded once muting is ended

- The muting status is displaying by the muting lamp, which is positioned on the top of the receiver.



- If the muting lamp is defective, the muting function cannot be activated. Any attempt to activate the function will immediately trigger the safety light grid and instantly switch off the OSSD; the muting lamp fault indicator will also light (see [Indicators for fault diagnostics](#) [ 57]).

- Muting cannot be activated when the safety light grid is in a safe condition (red LED is lit, protected field is interrupted).




Fig.: Timing diagram for L-type muting

Legend

t_{AB} : Time from the activation of the first sensor to the activation of the second sensor, max. 4 s

t_{Moff} : Once this time has elapsed, the muting function switches off automatically, max. 8 s





Fig.: Timing diagram for T-type muting

Legend

t_{AB} : Time from the activation of the first sensor to the activation of the second sensor, max. 4 s

Sequence for T-muting cycle when material passes from the right-hand side



Legend

- [1] Conveyed material on conveyor
- [2] First muting sensor on the input side
- [3] Second muting sensor on the input side
- [4] Safety light grid
- [5] Muting lamp
- [6] First muting sensor on the output side
- [7] Second muting sensor on the output side

Phase in the muting cycle	Explanation
	Material has already passed the first muting sensor and is being transported on the conveyor in the direction of the second muting sensor, muting lamp off.
	Material on the conveyor passes the second muting sensor (max. 4 s after the first sensor was passed). Muting lamp flashes, signalling the muting status.
	Material on the conveyor passes the safety light grid and the first muting sensor on the output side, muting lamp flashes, signalling the muting status.
	Material has left the area of the first muting sensor on the output side, muting lamp is off, muting status is ended. The next piece of material arrives at the first muting sensor.
	If material is transported from the left-hand side, the cycle is reversed. The output side becomes the input side and the flow starts with the second muting sensor on the output side.

4.5.2 Time monitoring - Timeout

Muting means a temporary suspension of the safety function. For this reason, the muting function must have a time restriction. When the muting sensors are activated and the muting status begins, an internal clock is started. If the muting sensors are still active after 10 minutes (status when delivered), the muting status is cancelled and the safety light grid switches to a safe condition.

Time monitoring for the muting function can be selected via DIP switches 1 and 5 (see [Setting the functions](#) [49]).



CAUTION!

Risk of injury due to loss of the safety function.

If time monitoring for the muting function is set to ∞ , the muting function is not cancelled until the muting sensors are no longer active.

This setting does not comply with the specifications of EN ISO 61496-1.

- Avoid a situation in which sustained muting is not detected.

4.6

Override

With the override function, a machine can be restarted even though material is interrupting one or more beams.

The reason for this is to clear the danger zone of any material that may have accumulated due to an error in the operating cycle.

For example, if there is a pallet in the protected field and the conveyor can no longer be switched on because the safety light curtain is keeping the OSSD switched off (because beams are interrupted), the accumulated material cannot be transported away from the zone.

Activating the override function allows intervention and enables the conveyor to be restarted.

The safety light curtain has two connections for override, which are connected via N/O contacts at 24 VDC (Override 1) and 0 VDC (Override 2). Both contacts are closed if the override function is activated.




Fig.: Timing diagram for override function

A key or automatic reset button is provided for activation.

Position the key or pushbutton so that when the override function is activated


- ▶ nobody can reach the danger zone and
- ▶ the position of the safety light curtain is unchanged.

If a pushbutton is used, the pushbutton must be operated until the protected field is totally clear.

The maximum time there may be between the two inputs Override 1 and 2 on operation is 400 ms.

▶ Requirement for activating the override function

- Safety light curtain has triggered and machine has stopped
- Muting lamp is not defective
- LED [3] top right flashes yellow:
- At least one muting sensor is active



▶ Automatic ending of override function

The override function is ended automatically when one of the following conditions is met:

- Muting timeout has elapsed
- The conditions necessary for activation are no longer present.
- Max. duration of override function has elapsed: After 120 s, the safety light curtain switches back to its normal operating state.
- No muting sensor is active
- No light beams are interrupted

4.7 Test function

The test function can be used to test the safety light grid. The reaction of the safety light grid corresponds to the reaction when a protected field is violated, but can be triggered by pressing the TEST/START button.




Fig.: Timing diagram for test function

4.8 Convert type without muting sensors to L/T-type

The safety light grids in the PSEN op4B/1 Series series are already capable of processing the data from muting sensors and can be upgraded to L or T-types using the muting sensors available as accessories.

Use the following item numbers for the upgrade:

PSEN op2.1 L-Muting Set	L-muting sensors to retrofit	630820
PSEN op2.2 T-Muting Set	T-muting sensors to retrofit	630821
PSEN op muting bracket kit	Mounting bracket for one muting sensor	630824
PSEN op cable M12 4-p. 0.75m L-muting	Connection cable for L-muting, 4-pole, shielded	630282
PSEN op cableset	Connection cable for T-muting, 4-pole, shielded	630295

5 Project configuration

5.1 Maintaining the safety distance

The minimum distance of the safety light grid to the hazardous machine component should be such that the operator cannot reach the danger zone until the movement of the hazardous machine part has stopped.

In accordance with the standards

- ▶ EN ISO 13855 (successor to EN 999) and
- ▶ TS-IEC 61496-4-3-CD:2012

this distance depends on four factors:

- ▶ Response time of the safety light grid
Time between the beams being effectively interrupted and the OSSDs switching off
- ▶ Machine's stopping time
Time it takes for the hazardous machine movement to effectively stop once the safety light grid switches off (including the reaction time of the connected relay)
- ▶ Approach speed
Speed at which the object (body) to be detected is nearing the danger zone in mm/s

The general formula for calculating the minimum distance (in accordance with TS-IEC 61496-4-3-CD2:2012) is:

$$S = K * (t_1 + t_2) + C$$

s	Minimum distance in mm, measured from the start of the protected field to the danger source.
K	Approach speed at which the object (body) to be detected is nearing the danger zone in mm/s K = 1600 mm/s when S > 500 mm K = 2000 mm/s when S ≤ 500 mm
t ₁	Response time of the safety light grid in seconds Time it takes for the signal at the OSSD output on the safety light curtain to change once a protected field has been violated
t ₂	Machine's stopping performance in seconds The time required for the machine to stop after the signal at the OSSD output changes
C	850 mm additional distance corresponding to the body resolution of the safety light grid

5.2 Ambient conditions

- ▶ Install the safety light grids in an environment that corresponds to the environmental data provided in the [Technical details](#) [64].
- ▶ Do not install the safety light grid close to particularly intense and/or flashing light sources; this applies in particular to the receiver.
- ▶ Avoid strong electromagnetic interference when operating the safety light grid.
- ▶ When operating the safety light grid, avoid the development of smoke, mist and dust that would reduce the operating range of the safety light grid.

5.3 Distance from reflective surfaces

If there are reflective surfaces close to the beams emitted from the safety light grid (whether from above, below or from the side) passive reflections can mean that an object within the protected field is not detected (see diagram).




Fig.: Interference to the function of the safety light grid due to reflective surfaces

Legend

- [1] Transmitter
- [2] Receiver
- [3] Reflective surface
- [4] Danger zone
- [5] Distance from safety light grid to reflective surface
- α Opening angle of the light beams emitted by the safety light grid

The receiver would detect the reflection from the reflective surface as a secondary beam, even if the main beam is interrupted by an existing object requiring detection.

As a result, the safety light grid must be installed at a minimum distance from reflective surfaces.

The minimum distance depends on two factors:

- ▶ Operating range between transmitter and receiver
- ▶ the maximum opening angle [64] of the light beams emitted by the safety light curtain at:
 $5^\circ = \pm 2.5^\circ$ in relation to the optical axis

Minimum distance for safety light grids

The formula for calculating the minimum distance D_{SR} for a safety light grid is:

- ▶ Operating range < 3 m: 0.15 m
- ▶ Operating range ≥ 3 m: $0.5 \times D_{OP}$ in m $\times \tan 2\alpha$




Fig.: Relationship between minimum distance and operating range - Type 4

Legend

D_{SR} : Minimum distance from reflective surfaces in m

D_{OP} : Operating range of the safety light grid in m

5.4

Installation of several adjacent safety light grids

If several adjacent safety light grids need to be installed, steps must be taken to ensure that the transmitter on one safety light grid does not interfere with the receiver on another safety light grid.

A layout as shown in the diagram below can cause problems because the light beams from the transmitter on the first safety light grid will influence the receiver on the second safety light grid.




Fig.: Non-permitted layout of two adjacent safety light grids

Positioning of several adjacent safety light grids:

- ▶ Both safety light grids must be oriented in opposite directions **or**
- ▶ An opaque surface must be positioned between two safety light grids.




Fig.: Permitted layout of two adjacent safety light grids - opposite orientation




Fig.: Permitted layout of two adjacent safety light grids – opaque surface between the safety light grids

Legend

[1]: Opaque surface

5.5 Use of deviating mirrors

Danger zones with different but adjacent access sides can be monitored using a safety light grid in conjunction with well-positioned deviating mirrors.

The diagram below shows an example solution for monitoring three different access sides using two deviating mirrors. The deviating mirrors must be positioned at an angle of 45° to the beams from the safety light grid.




Fig.: Example for using deviating mirrors

Legend

- [1] Receiver
- [2] Transmitter
- [3] Deviating mirrors
- [4] Danger zone
- [5] Light beams' path from transmitter to receiver
- [6] Distance from transmitter to deviating mirror, corresponds to the maximum effective operating range
- [7] Distance between deviating mirrors, corresponds to the maximum effective operating range, reduced by 15% for each mirror used
- [8] Distance from receiver to deviating mirror, corresponds to the maximum effective operating range
- [9] Minimum safety distance

When using deviating mirrors, please note:

- ▶ Even a minor angular displacement of the mirror can lead to misalignment, adversely affecting or preventing the function of the safety light grid. The [laser pointer \[73\]](#) available as an accessory should be used for alignment.
- ▶ The minimum safety distance [7] to the danger zone must be maintained for all sections of the beam.

- ▶ Use of a single deviating mirror reduces the effective operating range by about 15%. This percentage increases when two or more deviating mirrors are used (more detailed information is provided in the technical data for the relevant mirror). Please consider this reduction when positioning the safety light grid.
- ▶ You should not use more than three mirrors per device.
- ▶ Any dust or dirt on the mirror's reflective surface will drastically reduce the operating range.

5.6 Use of the muting function

Muting means a temporary suspension of the safety function and therefore an increased safety risk. A range of separate precautions must therefore be taken when using the muting function.

- ▶ Muting lamp
 - The muting lamp must be visible from all sides of the work area.
 - The muting lamp must be bright enough inside the work area.
 - The safety light grid must be wired correctly in order for the muting lamp to work correctly (see [Connector pin assignment](#) [ 44]).
- ▶ Use of the muting sensors restricts the operating range of the safety light grid. The achieved operating range must match or exceed the maximum width of the protected field.
 - Operating range of safety light grids with integrated muting sensors = 3 m
 - The operating range of safety light grids with external muting sensors, which use reflective sensors, or external muting sensors, which use transmitter and receiver sensors, depends on the type of the relevant muting sensor (see Technical details of the muting sensor).
- ▶ Prevent access to the danger zone during muting.
- ▶ The muting sensors
 - must detect material and allow it to pass,
 - must detect persons and, when the danger zone is accessed, trigger the OSSD and switch off the connected machine.



CAUTION!

Transport speed too low

If the transport speed is too low, the muting state is not triggered by passing material.

Select the transport speed so that the passing material passes both sensors within max. 4 s.

- ▶ Guarantee detection at all travel speeds that are intended to arise during operation.
- ▶ Prevent unintended activation of the muting sensors.
- ▶ Prevent manipulation of the muting sensors through simple means.
- ▶ Inform staff of the
 - hazard potential from the muting function,
 - the absence of protection during muting.
- ▶ Attach a notification sign close to the area protected by the safety light grid, so that it's clearly visible.
- ▶ The sign should indicate that there is no protection when the muting lamp is lit.
- ▶ Please note the following distances and times when installing the safety light grid and using the muting function.




Fig.: Distances between muting sensors in the application example - 4 muting sensors

Muting in two directions




Fig.: Distances between muting sensors - 4 muting sensors

Legend

[1] Safety light grid

A1 First muting sensor on the input side

B1 Second muting sensor on the input side

A2 First muting sensor on the output side

B2 Second muting sensor on the output side

Icon	Unit	Minimum value	Maximum value	Description
L	cm	$D_{MutingOff}$		Length of the object that triggers the muting status as it passes the muting sensors
V	cm/s	4.125	250	Speed at which the object is moving
D_{A-B}	cm	$< D_{MutingOff}$	Distance D_{A-B} must be covered in max. 4 s	Distance between the sensors connected to the same muting input A1 and B1, and between A2 and B2
$D_{MutingOff}$	cm	L		Distance between muting sensor A1 and the position from which the muting function is turned off again, when considering the transport direction from A1 to A2

Distances for muting with 4 sensors

Muting in one direction




Fig.: Distances between muting sensors - 2 muting sensors

Legend

[1] Safety light grid

A1 First muting sensor

B1 Second muting sensor

Icon	Unit	Minimum value	Maximum value	Description
L	cm	$D_{MutingOff}$		Length of the object that triggers the muting status as it passes the muting sensors
V	cm/s	4.125	250	Speed at which the object is moving
D_{A-B}	cm	$< D_{MutingOff}$	Distance must be covered within 4 s	Distance between the muting sensors A1 and B1
$D_{MutingOff}$	cm	L		Distance between muting sensor A1 and the position from which the muting function is turned off again

Distances for muting with 2 sensors

Muting in two directions with two muting sensors and cross muting

When cross muting is used, please note the following:

- ▶ The intersection point of the muting sensors must be behind the safety light grid, within the danger zone (see diagram).
- ▶ By arranging the muting sensors asymmetrically you ensure that the muting sensors must activate consecutively in order to activate a muting state (see diagram).




Fig.: Distances between muting sensors - Cross muting

Legend

[1] Safety light grid

A1 First muting sensor on the input side

B1 Second muting sensor on the input side

Display	Unit	Minimum value	Maximum value	Description
d2	cm		Distance must be covered within 4 s	Distance that the object covers from the first muting sensor A1 to the second muting sensor B2
D _{MutingOff}	cm	L		Distance between activation of the muting function and the position from which the muting function is switched off again

Distances for cross muting with 2 sensors

6 Installation and wiring

Please note the following when affixing the transmitter and receiver:


- ▶ The units' optical surfaces must be arranged so that they are facing each other.
- ▶ The connector sides of both units must be positioned on the same side and at the same height.
- ▶ The distance between the units must be within the operating range of the relevant unit (see [Technical details](#) [ 64]).

6.1 Attach safety light grid without muting sensors to mounting surface

Procedure

Attach the safety light grid to the mounting surface. Use the two threaded pins supplied to attach the units.

1. Insert the threaded pins into the grooves on both units.
2. Place a mounting bracket on the pins and secure the bracket with the pins.
3. Use screws to provisionally fix the mounting bracket to the mounting surface.
4. Align the safety light grid approximately and then tighten up the screws on the mounting bracket.



Where vibration is particularly strong

- ▶ threaded pins and
- ▶ mounting bracket

should be used with vibration dampers.


6.2 Attach safety light grid with muting sensors to mounting surface

Procedure

When the mounting profile (PSEN op Muting bracket Kit) is attached to the muting sensor:


Remove the mounting profile (PSEN op Muting bracket Kit) from the muting sensor.

Attach the mounting profile to the safety light grid (see drawing). Use the hexagonal screws to fix the mounting profile in the position required for using the muting sensors. Screw in the screws in the middle of the slot hole.



Attach the safety light grid to the mounting surface. It can be attached using the two threaded pins provided.

1. Insert the threaded pins into the grooves on the transmitter/receiver.
2. Place a mounting bracket on the pins and secure the bracket with the pins.
3. Use screws to provisionally fix the mounting bracket to the mounting surface.
4. Align the safety light grid approximately and then tighten up the screws on the mounting bracket.



Where there is particularly heavy vibration, vibration dampers can be used when installing the threaded pin and mounting bracket (see [Order reference for accessories](#) [71]).

6.3 Conversion of safety light grids without muting sensors

- ▶ Allocation of muting sensors to transmitter and receiver:

- The passive muting sensor PSEN op Reflector must be installed on the transmitter.
- The active muting sensor PSEN op Reflex must be installed on the receiver.


Requirement for installing the muting sensors on the safety light grid:

- ▶ The PSEN op muting bracket kit must be attached to both units of the safety light grid.
- ▶ The safety light grid must already be attached to the mounting surface.

Procedure

Check the position of the mounting profile on the safety light grid and slide the mounting profile on both units of the safety light grid along to the correct position of the muting sensor. To do this, loosen the hexagonal screws. Then tighten up the hexagonal screws again.


The mounting profiles should be at the same height.



[1] Mounting profile for attaching the muting sensor

[2] Safety light grid on mounting surface

Fix the muting sensor with the small plates to the mounting profile.



[1] Hexagonal screws for attaching the mounting profile to the safety light grid

[2] Allen screws for attaching the muting sensor to the mounting profile

6.4 Installation of external muting sensors

When using external muting sensors, position

- ▶ Sensor B1, with transport in one direction
- ▶ Sensors A2 and B1, with transport in two directions

As closely as possible to the safety light grid (see [Distances between muting sensors in the application example - 4 muting sensors](#)  37]).

6.5 Wiring

6.5.1 General guidelines

- ▶ Never place connection cables close to or in contact with cables with the following characteristics (motor supply, inverter or similar).
 - High current ratings,
 - Strong current fluctuations.
- ▶ Use separate cables to connect the wires to the OSSDs on different safety light grids.
- ▶ Do not connect contacts OSSD1 and OSSD2 in series or in parallel.
- ▶ Connect the N/C contact on the TEST/START button to the supply voltage on the safety light grid.
- ▶ Connect the N/C contact on the EDM to the supply voltage on the safety light grid.
- ▶ The safety light grid is already equipped with internal filter capacitors. We would advise against using additional external components.

Use the connection cable available as an accessory to wire the safety light grid (see [Order reference for accessories](#) [ 71]).

6.5.2 Connector pin assignment

Electrical connections to the transmitter and receiver are made via M12 connectors on both units. These connectors are located on the bottom of the units.




Fig.: 5-pin connector on the receiver to connect muting sensors to the receiver on the safety light grid

PIN	Designation	Description	Cable colour
1	+24 VDC	Supply voltage for external muting sensor	Brown
2	Muting 2	Input signal for second muting sensor	White
3	0 VDC	Supply voltage for external muting sensor	Blue
4	Muting 1	Input signal for first muting sensor	Black
5	n.c.	-	Grey

- ▶ n.c. = not connected




Fig.: 8-pin connector on the receiver to connect receiver to supply voltage and evaluation device

PIN	Designation	Description	Cable colour
1	TEST/RESET	TEST/START button	White
2	+24 VDC	Supply voltage for receiver on the safety light grid	Brown
3	Override 1	N/O contact to override muting sensor input 1	Green
4	EDM	N/C contact for feedback loop monitoring (to ensure that downstream consumers are disconnected)	Yellow
5	OSSD1	Pulsed safety output 1	Grey
6	OSSD2	Pulsed safety output 2	Pink
7	0 VDC	Supply voltage for receiver on the safety light grid	Blue
8	Override 2	N/O contact to override muting sensor input 2	red




Fig.: 4-pin connector on the transmitter to connect transmitter to supply voltage

PIN	Designation	Description	Cable colour
1	+24 VDC	Supply voltage for transmitter	Brown
2	n.c.	-	White
3	0 VDC	Supply voltage for transmitter	Blue
4	n.c.	-	Black

► n.c. = not connected




Fig.: 5-pin connector on the transmitter to connect the supply voltage for muting sensors to the transmitter on the safety light grid

PIN	Designation	Description	Cable colour
1	+24 VDC	Supply voltage for external muting sensor	Brown
2	n.c.	-	White
3	0 VDC	Supply voltage for external muting sensor	Blue
4	n.c.	-	Black
5	n.c.	-	Grey

► n.c. = not connected

6.5.3 TEST/START button

Connect the N/C contact on the TEST/START button to the supply voltage on the safety light grid.


6.5.4 EDM

Connect the N/C contact on the EDM to the supply voltage on the safety light grid.

6.5.5 Earthing the safety light grid

Attach the earth connection in the drill hole provided on the connector side of the safety light curtain using the screw provided (see diagram).

Identify the earthing contact using the adhesive label provided.



Legend:

[1]: Drill holes for earthing screw. The drill holes are on the bottom of the safety light grid, at the same height on the right and left.

6.5.6 Connections for muting

Wire the muting sensors using the connection cable provided (see [Order reference for accessories, section on muting accessories](#) [ 73]).

- ▶ For L-muting:
PSEN op cable M12 4-p. 0.75m L-muting
- ▶ For T-muting and for cross muting:
PSEN op cableset

The connection cable is used to

- ▶ Connect the muting sensors to the safety light grid
- ▶ Supply voltage to the muting sensors via the safety light grid.

Wire the muting sensors as shown in the following diagrams.




Fig.: Wiring of 4 muting sensors on the receiver's 5-pin connector




Fig.: Wiring of 2 muting sensors on the receiver's 5-pin connector




Fig.: Wiring of 2 muting sensors for cross muting on the receiver's 5-pin connector

Earthing of muting sensors

Attach the earth connection in the drill hole provided on the side of the muting sensors, using the screw provided. The drill holes for the earthing screw are on the right and left side of the muting sensors, at the same height.

Identify the earthing contact using the adhesive label provided.

6.5.7

Wiring of external sensors on the safety light grid

Wire the external muting sensors in the control cabinet in accordance with the details stated under Connections for muting.

7 Commissioning

7.1 Setting the functions

7.1.1 Open DIP switch cover

The DIP switches must be operated to set the functions of the safety light grid.




Fig.: Open DIP switch cover

Legend:

[1]: Groove on the DIP switch cover

Procedure:

1. Insert a thin blade slotted-head screwdriver into the groove on the cover horizontally and at a right angle to the safety light grid (see diagram).
2. Gently press the tip of the screwdriver downwards and lever the cover open.

7.1.2 Activate muting

Muting only needs to be activated in the case of L-muting.

Procedure for activating L-muting

1. Switch muting to L-muting on the DIP switch.
Set DIP switches 2 and 6 to OFF.




Fig.: DIP switches 2 and 6 in OFF position = L-muting activated

To use muting, the following requirements apply:

- ▶ the muting lamp must not be defective,
- ▶ the muting inputs must be wired correctly (see [Connector pin assignment \[44\]](#)),
- ▶ the safety light grid must be in normal operation.

If any of these requirements are not met, the safety light grid switches immediately to a safe condition when supply voltage is switched on.

7.1.3 Set muting timeout

Time monitoring for the muting function can be set to

- ▶ 10 minutes or
- ▶ to ∞

gestellt werden.

When the unit is delivered, this is already preset to 10 minutes.



CAUTION!

Risk of injury due to loss of the safety function.

If time monitoring for the muting function is set to ∞ , the muting function is not cancelled until the muting sensors are no longer active.

This setting does not comply with the specifications of EN ISO 61496-1.

- Avoid a situation in which sustained muting is not detected.

Procedure for setting to ∞

Set DIP switches 1 and 5 to OFF.

7.1.4 Activate EDM

EDM only needs to be activated if the contactors are controlled directly.

Procedure for activating EDM

1. Connect the inputs of the external control elements.
Connect the inputs to a N/C contact with 24 VDC on the device to be monitored.
2. Activate EDM on the DIP switch.
Set DIP switches 3 and 7 to OFF.




Fig.: DIP switch 3 and 7 in OFF position = EDM activated

7.1.5 Restart after unit is triggered

Select how the restart is controlled after the OSSDs have been switched off.

- ▶ Without restart interlock
Status when delivered
- ▶ With restart interlock
Set DIP switches 4 and 8 to OFF.




Fig.: DIP switches 4 and 8 in OFF position = With restart interlock


7.2 Orientation

7.2.1 General guidelines

For the safety light grid to function properly, the transmitter and receiver must be aligned.

Optimum alignment is achieved when the optical axes of the first and last beam from the transmitter coincide with the optical axes of the corresponding elements on the receiver.

The positions of the transmitter and receiver on the safety light grid, and the muting sensors if present, can be modified in accordance with the following diagram.



The yellow LEDs High Align [3] and Low Align [4] indicate the status of the alignment.

	▶ If the alignment for the upper beam is correct, the LED High Align [3] will light ▶ If the alignment for the lower beam is correct, the LED Low Align [4] will light ▶ If both beams are aligned correctly and the LEDs are lit, the green LED will also light [1]
--	--

The alignment of a type without muting set is described under Safety light grid alignment.

When commissioning an L or T-type or external muting sensors, this alignment must also be carried out, followed by alignment of the muting sensors.



INFORMATION

For simple, precise alignment of the safety light grid and muting sensors we recommend the use of the laser pointer (order no. 630 340).

Particularly where there are:

- difficult environmental conditions
- large distances between the safety light grid's receiver and transmitter

7.2.2

Safety light grid alignment

Prerequisites

- ▶ Transmitter and receiver are inserted correctly in a suitable place
- ▶ Wiring has been carried out correctly
- ▶ Supply voltage is switched off
- ▶ Protected field is clear

Procedure

1. Press the TEST/START button and keep the button pressed down.
2. Switch on the supply voltage to the safety light grid.
3. Release the TEST/START button.
4. Prevent anyone from accessing the protected field during the whole time that alignment takes place.
5. Check that the lower, green LED and the yellow LED on the transmitter are lit. The transmitter is ready for operation and is working correctly.
6. Start the alignment if the red LED is lit (incorrect alignment). If the green LED and both yellow LEDs are lit, the alignment is already correct.
 - Hold the receiver steady and align the transmitter so that the lower yellow LED is lit. This means that the lower beam is aligned.
 - Rotate the transmitter around the light axis of the lower lens until the upper yellow LED is also lit, the red LED goes out and the green LED lights.
 - Check that the green LED is permanently lit.


7. Tighten up all the fixing screws.
8. Switch the supply voltage to the safety light grid off and then on again.
9. Check that the green LED on the receiver is lit.
10. Check that the safety light grid operates correctly.

If a single light beam is interrupted by an opaque object

- the green LED must go out,
- the red LED must light and
- the safety light grid must switch to a safe condition.

7.2.3 Muting sensor alignment

1. Check that the safety light grid is aligned correctly and that the safety light grid is in normal operation. The green LED on the receiver, the yellow LED on the transmitter and the two yellow LEDs on the receiver must light.
2. Use the LED to check the alignment of the muting sensors.
3. Modify the position of the muting sensors on the safety light grid until the red LEDs on the sensors go out (see diagram).
 - Vertical alignment of the muting sensors: Undo the hexagonal screws and move the mounting profile upwards.
 - Horizontal alignment of the muting sensors: Loosen the hexagonal screws and move the mounting profile within the slot hole for the hexagonal screws.



Legend:

- [1]: Move the muting sensor upwards on the mounting profile for vertical alignment
- [2]: Move the muting sensor within the slot hole for horizontal alignment

7.2.4 LED support during alignment

Display	LED	Designation	Status	Meaning
	[1]	Normal Operation	Lights green	Transmitter and receiver are correctly aligned and the protected field is clear
	[2]	OSSD	Lights red	Transmitter and receiver are not correctly aligned or protected field is interrupted by an opaque object
	[3]	Restart/Align	Lights yellow	Final upper light beam is aligned with the receiver lens opposite
	[4]	Align	Lights yellow	Final lower light beam is aligned with the receiver lens opposite

LED indicators on the receiver – Meaning during alignment

7.3 Checking the safety light grid

Once the safety light grid has been installed and aligned, final inspections must be carried out before it can be put into service.



INFORMATION

This inspection may only be carried out by qualified personnel.

- ▶ Check that the safety light grid, including any existing muting sensors, are aligned and attached correctly. The red LED should not light up if gentle pressure is applied to the edges of the safety light grid.
- ▶ Check that the safety distance complies with the requirements stated in Maintaining the safety distance.
- ▶ Check that the area between the safety light grid and the hazardous machine component is inaccessible from all sides.
- ▶ Check that the safety light grid cannot be impaired by external light sources.
- ▶ Check that, once switched on, the safety light grid switches to a safe condition if the protected field is accessed.
- ▶ Violate the protected field and check that
 - the OSSDs are switched off,
 - the red LED lights
 - the monitored machine is shut down.

- ▶ Check that the safety light grid's response time and the machine's stopping performance meet the specifications stated under Maintaining the safety distance.
- ▶ If muting sensors are installed:
Check that the muting sensors operate correctly. Access the protected field covered by the muting sensors.
 - The muting lamp on the safety light grid must light.
 - The red LEDs on the muting sensors must light.
 - The OSSDs must be switched off.
 - The monitored machine must be shut down.

7.4 System connection

This section provides information on how to connect the safety light grid to an evaluation device.


A safety relay from the PNOZsigma series (PNOZ s4, PNOZ s5) can be used as the evaluation device, for example. The wiring is described in the operating instructions for the PNOZsigma device.

8 Operation


8.1 Status information during operation

The operating state of the safety light grid is displayed using LEDs:

- ▶ four LEDs on the receiver and
- ▶ two LEDs on the transmitter.

Display	LED	Designation	Status	Meaning
	[1]	Normal Operation	Lights green	Safety light grid in operation, no objects detected
	[2]	OSSD	Lights yellow	Object has been detected, OSSDs are in an OFF state
	[3]	Restart/Align	Lights red	Irrelevant during normal operation ▶ In operating mode with restart interlock: Object has been detected, safety light grid is in a safe condition ▶ During alignment: LED support during alignment [ 54]
	[4]	Align	Lights yellow	Irrelevant during normal operation ▶ During alignment: LED support during alignment [ 54]
	[1]	Normal Operation	Off	Override can be performed. Activate the override function and make sure that the protected field is clear.
	[2]	OSSD	Lights red	
	[3]	Restart/Align	Flashes yellow	
	[4]	Align	Off	

LED indicators during normal operation - Receiver

Display	LED	Designation	Status	Meaning
	[1]	Power	Lights green	Supply voltage correct
	[2]	Status	Lights yellow	Safety light grid is transmitting light beams

LED indicators during normal operation - Transmitter

8.2 Perform test

Prerequisites

- ▶ Safety light grid is in operation
- ▶ Correct function of safety light grid



Procedure






Press the TEST/START button for at least 0.5 seconds.

- ▶ The OSSDs switch off, the red LED lights and the connected machine stops.



8.3 Diagnostics and troubleshooting

8.3.1 Indicators for fault diagnostics

Display	LED	Status	Meaning	Action
	[1]	Off	Functional error on the OSSD	Check the connected OSSDs. Make sure that the load corresponds to the information stated in the Technical details [64] .
	[2]	Flashes red		
	[3]	Flashes yellow		
	[4]	Flashes yellow		
	[1]	Off	Functional error on the connected output signal switching devices (EDM test failed)	Check the connected output signal switching devices. The response times of the output signal switching devices must be compatible with the timing diagram for the safety light grid's test function. Switch the safety light grid off and then on again. If the display is unchanged, swap the external switching device.
	[2]	Flashes red		
	[3]	Off		
	[4]	Flashes yellow		

Display	LED	Status	Meaning	Action
	[1]	Off	Functional error on the safety light grid	Check the correct position of the DIP switches. The positions of the DIP switches must match the intended configuration.
	[2]	Off		
	[3]	Flashes yellow		
	[4]	Flashes yellow		
	[1]	Off	Functional error on override	Check the wiring of the override function. If the display is unchanged, contact Pilz.
	[2]	Lights red		
	[3]	Flashes yellow		
	[4]	Flashes yellow		
	[1]	Off	Optical error	Check the alignment of the transmitter to the receiver Switch the safety light grid off and then on again. If the display is unchanged, contact Pilz.
	[2]	Off		
	[3]	Off		
	[4]	Flashes yellow		
	[1]	Flashes red	Functional error on muting display	Switch the safety light grid off and then on again. If the display is unchanged, contact Pilz.
	[2]	Off		
	[3]	Flashes green		
	[4]	Flashes yellow		
	[1]	Flashes red	Supply voltage outside the permitted range (see Technical details [ 64])	Check that the supply voltage complies with the information stated in the Technical details [ 64]. Switch the safety light grid off and then on again. If the display is unchanged, contact Pilz.
	[2]	Off		
	[3]	Flashes green		
	[4]	Flashes yellow		

LED indicators in fault condition - Receiver

Display	LED	Status	Meaning	Action
	[1]	Lights green	General transmitter error	Check that the supply voltage complies with the information stated in the Technical details [64] . Switch the safety light grid off and then on again.
	[2]	Flashes yellow		
	[1]	Off	Supply voltage outside the permitted range (see Technical details [64])	If the display is unchanged, contact Pilz.
	[2]	Off		
	[1]	Lights green	Supply voltage outside the permitted range (see Technical details [64])	
	[2]	Off		

LED indicators in fault condition - Transmitter

8.3.2

Perform reset

Prerequisites

- ▶ Incorrect function of safety light grid
- ▶ There must be nobody within the danger zone

Procedure

Press the TEST/START button for at least 5 seconds and then release it.

- ▶ The OSSDs switch on, the green LED lights and the connected machine starts up.

9 Regular checks and maintenance

9.1 Checks

9.1.1 Regular checks

Regular checks can bring to light changes to the plant/machine, safeguards and ambient conditions.

9.1.2 Daily check

The safety light grid must undergo a function test once a day (e.g. when starting work, after a shift change).



INFORMATION

This inspection may only be carried out by qualified personnel.

Check the safety function of the safety light grid as follows:

Violate the protected field. The indicator light unit must change from green to red and the movement causing the hazard must be switched off.

9.1.3 Check after plant/machine modification

Check the safety light grid each time the plant/machine is modified. Changing the safety light grid or swapping safety light grid components should be regarded as a modification. The requirements of the applicable national regulations must be observed **absolutely**.



INFORMATION

This inspection may only be carried out by qualified personnel.

The Appendix contains a Checklist which should help you perform the safety check.

9.2 Maintenance

Other than cleaning the lens covers, the safety light curtains requires no other form of maintenance.



CAUTION!

Improper cleaning agents can damage the safety light curtain and lead to malfunctions.

Moist cotton cloths should be used for cleaning.

Avoid using

- ▶ Alcohol,
- ▶ Solvents,
- ▶ Cloths made of wool,
- ▶ Cloths made of synthetic material.

Clean the lens covers during the regular check of the safety light curtain.

10 Dimensions

Safety light grid without integrated muting sensors




Fig.: Receiver





Fig.: Transmitter


Legend

- [1] Height of protected field
- [2] Position of first light beam
- [3] Position of last light beam

Safety light grid with L-muting set



Safety light grid with T-muting set



11 Technical details

Safety light grid without integrated muting sensors

General	630800	630801
Certifications	CE, TÜV, cULus Listed	CE, TÜV, cULus Listed
ESPE type	4	4
Sensor's mode of operation	Optical	Optical
Protected field height	515 mm	815 mm
Resolution		
Protection type	Object	Object
Operating range	0,5 - 50 m	0,5 - 50 m
Detection capability	515 mm	415 mm
Electrical data	630800	630801
Supply voltage		
Voltage	24 V	24 V
Kind	DC	DC
Max. power consumption receiver	2,2 W	2,2 W
Max. power consumption transmitter	0,9 W	0,9 W
Optical data	630800	630801
Opening angle	-2,5 - 2,5 deg	-2,5 - 2,5 deg
Used wavelength range	880 nm	880 nm
No. of beams	2	3
Inputs	630800	630801
Max. overall line capacitance C _{lmax}	65 nF	65 nF
Semiconductor outputs	630800	630801
OSSD safety outputs	2	2
Switching current per output	500 mA	500 mA
Times	630800	630801
Response time t ₁	14 ms	14 ms
Environmental data	630800	630801
Ambient temperature		
Temperature range	-10 - 55 °C	-10 - 55 °C
Storage temperature		
Temperature range	-25 - 70 °C	-25 - 70 °C
Climatic suitability		
Humidity	95 % r. h. at 50 °C	95 % r. h. at 50 °C
Condensation during operation	Not permitted	Not permitted
Vibration		
in accordance with the standard	EN 60068-2-6	EN 60068-2-6
Frequency	10 - 55 Hz	10 - 55 Hz
Amplitude	0,35 mm	0,35 mm

Environmental data		
	630800	630801
Shock stress		
in accordance with the standard	EN 60068-2-29	EN 60068-2-29
Acceleration	10g	10g
Duration	16 ms	16 ms
Airgap creepage		
Pollution degree	2	2
Protection type		
in accordance with the standard	EN 60529	EN 60529
Housing	IP65	IP65
Mechanical data		
	630800	630801
Connection type		
Receiver	M12, 5-pin male connector; M12, 8-pin male connector	M12, 5-pin male connector; M12, 8-pin male connector
Transmitter	M12, 4-pin male connector; M12, 5-pin male connector	M12, 4-pin male connector; M12, 5-pin male connector
Material		
Top	Aluminium	Aluminium
Dimensions		
Height	653 mm	953 mm
Width	35 mm	35 mm
Depth	41,2 mm	41,2 mm
Weight	2.600 g	3.500 g
General		
	630802	630803
Certifications	CE, TÜV, cULus Listed	CE, TÜV, cULus Listed
ESPE type	4	4
Sensor's mode of operation	Optical	Optical
Protected field height	915 mm	1.215 mm
Resolution		
Protection type	Object	Object
Operating range	0,5 - 50 m	0,5 - 50 m
Detection capability	315 mm	415 mm
Electrical data		
	630802	630803
Supply voltage		
Voltage	24 V	24 V
Kind	DC	DC
Max. power consumption receiver	2,2 W	2,2 W
Max. power consumption transmitter	0,9 W	0,9 W
Optical data		
	630802	630803
Opening angle	-2,5 - 2,5 deg	-2,5 - 2,5 deg
Used wavelength range	880 nm	880 nm
No. of beams	4	4

Inputs	630802	630803
Max. overall line capacitance C _{lmax}	65 nF	65 nF
Semiconductor outputs	630802	630803
OSSD safety outputs	2	2
Switching current per output	500 mA	500 mA
Times	630802	630803
Response time t ₁	16 ms	16 ms
Environmental data	630802	630803
Ambient temperature		
Temperature range	-10 - 55 °C	-10 - 55 °C
Storage temperature		
Temperature range	-25 - 70 °C	-25 - 70 °C
Climatic suitability		
Humidity	95 % r. h. at 50 °C	95 % r. h. at 50 °C
Condensation during operation	Not permitted	Not permitted
Vibration		
in accordance with the standard	EN 60068-2-6	EN 60068-2-6
Frequency	10 - 55 Hz	10 - 55 Hz
Amplitude	0,35 mm	0,35 mm
Shock stress		
in accordance with the standard	EN 60068-2-29	EN 60068-2-29
Acceleration	10g	10g
Duration	16 ms	16 ms
Airgap creepage		
Pollution degree	2	2
Protection type		
in accordance with the standard	EN 60529	EN 60529
Housing	IP65	IP65
Mechanical data	630802	630803
Connection type		
Receiver	M12, 5-pin male connector; M12, 8-pin male connector	M12, 5-pin male connector; M12, 8-pin male connector
Transmitter	M12, 4-pin male connector; M12, 5-pin male connector	M12, 4-pin male connector; M12, 5-pin male connector
Material		
Top	Aluminium	Aluminium
Dimensions		
Height	1.053 mm	1.353 mm
Width	35 mm	35 mm
Depth	41,2 mm	41,2 mm
Weight	3.600 g	4.400 g

Safety light grid with integrated muting sensors for muting in one or two directions

General	630808	630809
Certifications	CE, TÜV, cULus Listed	CE, TÜV, cULus Listed
ESPE type	4	4
Sensor's mode of operation	Optical	Optical
Protected field height	515 mm	815 mm
Resolution		
Protection type	Object	Object
Operating range	0,5 - 3 m	0,5 - 3 m
Detection capability	515 mm	415 mm
Electrical data	630808	630809
Supply voltage		
Voltage	24 V	24 V
Kind	DC	DC
Max. power consumption receiver	2,2 W	2,2 W
Max. power consumption transmitter	0,9 W	0,9 W
Optical data	630808	630809
Opening angle	-2,5 - 2,5 deg	-2,5 - 2,5 deg
Used wavelength range	880 nm	880 nm
No. of beams	2	3
Inputs	630808	630809
Max. overall line capacitance C _{lmax}	65 nF	65 nF
Semiconductor outputs	630808	630809
OSSD safety outputs	2	2
Switching current per output	500 mA	500 mA
Times	630808	630809
Response time t ₁	14 ms	14 ms
Environmental data	630808	630809
Ambient temperature		
Temperature range	-10 - 55 °C	-10 - 55 °C
Storage temperature		
Temperature range	-25 - 70 °C	-25 - 70 °C
Climatic suitability		
Humidity	95 % r. h. at 50 °C	95 % r. h. at 50 °C
Condensation during operation	Not permitted	Not permitted
Vibration		
in accordance with the standard	EN 60068-2-6	EN 60068-2-6
Frequency	10 - 55 Hz	10 - 55 Hz
Amplitude	0,35 mm	0,35 mm

Environmental data		
	630808	630809
Shock stress		
in accordance with the standard	EN 60068-2-29	EN 60068-2-29
Acceleration	10g	10g
Duration	16 ms	16 ms
Airgap creepage		
Pollution degree	2	2
Protection type		
in accordance with the standard	EN 60529	EN 60529
Housing	IP65	IP65
Mechanical data		
	630808	630809
Connection type		
Receiver	M12, 5-pin male connector; M12, 8-pin male connector	M12, 5-pin male connector; M12, 8-pin male connector
Transmitter	M12, 4-pin male connector; M12, 5-pin male connector	M12, 4-pin male connector; M12, 5-pin male connector
Material		
Top	Aluminium	Aluminium
Dimensions		
Height	653 mm	953 mm
Width	35 mm	35 mm
Depth	41,2 mm	41,2 mm
Weight	4.200 g	5.100 g
General		
	630810	630811
Certifications	CE, TÜV, cULus Listed	CE, TÜV, cULus Listed
ESPE type	4	4
Sensor's mode of operation	Optical	Optical
Protected field height	515 mm	815 mm
Resolution		
Protection type	Object	Object
Operating range	0,5 - 3 m	0,5 - 3 m
Detection capability	515 mm	415 mm
Electrical data		
	630810	630811
Supply voltage		
Voltage	24 V	24 V
Kind	DC	DC
Max. power consumption receiver	2,2 W	2,2 W
Max. power consumption transmitter	0,9 W	0,9 W
Optical data		
	630810	630811
Opening angle	-2,5 - 2,5 deg	-2,5 - 2,5 deg
Used wavelength range	880 nm	880 nm
No. of beams	2	3

Inputs	630810	630811
Max. overall line capacitance C _{lmax}	65 nF	65 nF
Semiconductor outputs	630810	630811
OSSD safety outputs	2	2
Switching current per output	500 mA	500 mA
Times	630810	630811
Response time t ₁	14 ms	14 ms
Environmental data	630810	630811
Ambient temperature		
Temperature range	-10 - 55 °C	-10 - 55 °C
Storage temperature		
Temperature range	-25 - 70 °C	-25 - 70 °C
Climatic suitability		
Humidity	95 % r. h. at 50 °C	95 % r. h. at 50 °C
Condensation during operation	Not permitted	Not permitted
Vibration		
in accordance with the standard	EN 60068-2-6	EN 60068-2-6
Frequency	10 - 55 Hz	10 - 55 Hz
Amplitude	0,35 mm	0,35 mm
Shock stress		
in accordance with the standard	EN 60068-2-29	EN 60068-2-29
Acceleration	10g	10g
Duration	16 ms	16 ms
Airgap creepage		
Pollution degree	2	2
Protection type		
in accordance with the standard	EN 60529	EN 60529
Housing	IP65	IP65
Mechanical data	630810	630811
Connection type		
Receiver	M12, 5-pin male connector; M12, 8-pin male connector	M12, 5-pin male connector; M12, 8-pin male connector
Transmitter	M12, 4-pin male connector; M12, 5-pin male connector	M12, 4-pin male connector; M12, 5-pin male connector
Material		
Top	Aluminium	Aluminium
Dimensions		
Height	653 mm	953 mm
Width	35 mm	35 mm
Depth	41,2 mm	41,2 mm
Weight	5.600 g	6.500 g

Where standards are undated, the 2023-05 latest editions shall apply.

11.1 Safety characteristic data



NOTICE

You must comply with the safety characteristic data in order to achieve the required safety level for your plant/machine.

Operating mode	EN ISO 13849-1: 2015	EN ISO 13849-1: 2015	EN IEC 62061 SIL CL/max.	EN IEC 62061 61508	EN/IEC 61511 61508	EN/IEC 61511 61508	EN ISO 13849-1: 2015
	PL	Category	SIL	PFH _D [1/h]	SIL	PFD	T _M [year]
2-ch. OSSD	PL e	Cat. 4	SIL 3	2,62E-09	SIL 3	–	20

Explanatory notes for the safety-related characteristic data:

- T_M is the maximum mission time in accordance with EN ISO 13849-1. The value also applies as the retest interval in accordance with EN/IEC 61508-6 and EN/IEC 61511 and as the proof test interval and mission time in accordance with EN IEC 62061

All the units used within a safety function must be considered when calculating the safety characteristic data.



INFORMATION

A safety function's SIL/PL values are **not** identical to the SIL/PL values of the units that are used and may differ from these.

12 Order reference

12.1 Order reference for safety light grids

Product type	Features	Order no.
PSEN op4B-2-050/1	Safety light curtain with body resolution, protected field height 500 mm	630800
PSEN op4B-3-080/1	Safety light curtain with body resolution, protected field height 800 mm	630801
PSEN op4B-4-090/1	Safety light curtain with body resolution, protected field height 900 mm	630802
PSEN op4B-4-120/1	Safety light curtain with body resolution, protected field height 1200 mm	630803
PSEN op4B-L-050/1	Safety light curtain with body resolution, with integrated muting sensors (in one direction), protected field height 500 mm	630808
PSEN op4B-L-080/1	Safety light curtain with body resolution, with integrated muting sensors (in one direction), protected field height 800 mm	630809
PSEN op4B-T-050/1	Safety light curtain with body resolution, with integrated muting sensors (in two directions), protected field height 500 mm	630810
PSEN op4B-T-080/1	Safety light curtain with body resolution, with integrated muting sensors (in two directions), protected field height 800 mm	630811

12.2 Order reference for accessories

Safety light curtain accessories

Product type	Features	Order no.
PSEN op Protective Column-060/1	Protective column for safety light curtain, H = 600 mm	630950
PSEN op Protective Column-090/1	Protective column for safety light curtain, H = 900 mm	630951
PSEN op Protective Column-120/1	Protective column for safety light curtain, H = 1200 mm	630952
PSEN op Protective Column-165/1	Protective column for safety light curtain, H = 1650 mm	630953
PSEN op Protective Column-190/1	Protective column for safety light curtain, H = 1900 mm	630954
PSEN op Protective Base/1	Floor bracket	630955
PSEN op Bracket kit antivibration	Vibration damper	630327

Product type	Features	Order no.
PSEN op Protective Column 2-050/1	Protective column with deviating mirror, H = 500 mm	630961
PSEN op Protective Column 3-080/1	Protective column with deviating mirror, H = 800 mm	630962
PSEN op Protective Column 4-090/1	Protective column with deviating mirror, H = 900 mm	630963
PSEN op Protective Column 4-120/1	Protective column with deviating mirror, H = 1200 mm	630964
Laser pointer for PSEN 4/2	Laser pointer	630340
PSEN op cable axial M12 4-pole 3m	Connection cable for light barriers, 4-pole, unshielded, 3 m	630300
PSEN op cable axial M12 4-pole 5m	Connection cable for light barriers, 4-pole, unshielded, 5 m	630301
PSEN op cable axial M12 4-pole 10m	Connection cable for light barriers, 4-pole, unshielded, 10 m	630302
PSEN op cable axial M12 4-pole 30m	Connection cable for light barriers, 4-pole, unshielded, 30 m	630296
PSEN op cable axial M12 4-pole 50m	Connection cable for light barriers, 4-pole, unshielded, 50 m	630362
PSEN op cable axial M12 5-pole 3m	Connection cable for light barriers, 5-pole, unshielded, 3 m	630310
PSEN op cable axial M12 5-pole 5m	Connection cable for light barriers, 5-pole, unshielded, 5 m	630311
PSEN op cable axial M12 5-pole 10m	Connection cable for light barriers, 5-pole, unshielded, 10 m	630312
PSEN cable M12-5sf 20m	Connection cable for light barriers, 5-pole, unshielded, 20 m	630298
PSEN op cable axial M12 5-pole 30m	Connection cable for light barriers, 5-pole, unshielded, 30 m	630297
PSEN op cable axial M12 5-pole 50m	Connection cable for light barriers, 5-pole, unshielded, 50 m	630364
PSEN op cable axial M12 8-p. shield. 3 m	Connection cable for light barriers, 8-pole, shielded, 3 m	630313
PSEN op cable axial M12 8-p. shield. 5 m	Connection cable for light barriers, 8-pole, shielded, 5 m	630314
PSEN op cable axial M12 8-p. shield. 10 m	Connection cable for light barriers, 8-pole, shielded, 10 m	630315
PSEN op cable axial M12 8-p. shield. 30 m	Connection cable for light barriers, 8-pole, shielded, 30 m	630328
PSEN op cable axial M12 8-p. shield. 50 m	Connection cable for light barriers, 8-pole, shielded, 50 m	630368

Muting accessories

Product type	Features	Order no.
PSEN op2.3 L-Reflex	Single active muting sensor (without mounting bracket)	630822
PSEN op2.4 L-Reflector	Single passive muting sensor (without mounting bracket)	630823
PSEN op3.2 Emitter M12	External muting sensor, transmitter	630832
PSEN op3.1 Receiver NO/NC M12	External muting sensor, receiver	630831
PSEN op3.3 Reflex NO/NC M12	External muting sensor (reflex light sensor)	630830

PSEN op2.1 L-Muting Set	L-muting sensors to retrofit	630820
PSEN op2.2 T-Muting Set	T-muting sensors to retrofit	630821
PSEN op muting bracket kit	Mounting bracket for one muting sensor	630824
PSEN op cable M12 4-p. 0.75m L-muting	Connection cable for L-muting, 4-pole, shielded	630282
PSEN op cableset	Connection cable for T-muting, 4-pole, shielded	630295

13 Appendix

13.1 Check list

Note that the check list is not intended to replace the plant-specific safety analysis required for commissioning/recommissioning, nor the resulting inspections and actions.



INFORMATION

Commissioning, recommissioning and regular inspection may only be carried out by qualified personnel.

We recommend that you keep the completed check list and store it with the machine documentation for reference.

No.	Action	OK	NOT OK	Notes
1	Check the category/standards			
	Does the category of the safety light grid match the category required for the plant/machine?			
	Have the standards applicable for the plant/machine been considered?			
2	Environmental conditions for checking the safety light grid			
	Have the technical details been met for all the safety light grid components?			
3	Check access to the danger zone Are all access points to the danger zone safeguarded either by safety light grids or by mechanical safeguards?			
4	Check minimum distance to danger zone			
	Has the minimum distance been calculated in accordance with the applicable standards?			
	Has the calculated minimum distance been maintained at all points?			
5	Check protected field			
	Has the ability to creep underneath the protected field undetected been excluded?			

No.	Action	OK	NOT OK	Notes
6	Check safety light grid			
	Make sure that there are no objects in front of the safety light grid (e.g. trailing cable, crossbeams, struts, covers).			
	Make sure that there are no transparent materials between the monitored protected field and the safety light grid (e.g. glass panel).			
	Are all the mechanical connections on the safety light grid attached correctly?			
	Are all the electrical connections to the safety light grid wired correctly?			
7	Check start/reset interlock			
	Check control device (e.g. PITenable, PIT-jog).			
	Is there a control device to release the start/restart interlock?			
	Is the control device positioned correctly?			
	Is the control device installed and wired correctly?			
8	Check the effectiveness of the safety light grid during the hazardous movement Is the safety light grid effective throughout the whole of the plant/machine's hazardous movement?			
9	Check the output circuitry of the programmable safety and control system			
	Have the outputs that have been defined as OSSDs been incorporated in accordance with the required category?			
	Are the switching elements that are connected to the outputs (e.g. valves, contactors) monitored via feedback loops?			
	Does the wiring of the outputs match the circuit diagram?			
10	Switch on safety light grid When you switch on, is it necessary to operate the control device for the start-up interlock before the plant/machine can start up?			
11	Switch off safety light grid Is the hazardous movement stopped immediately when you switch off?			

No.	Action	OK	NOT OK	Notes
12	Check guard function for protected field of the safety light grid: Violate the protected field at various points: The hazardous movement must be shut down. Check that the start/restart interlock is working correctly.			

14 **EC declaration of conformity**

This product/these products meet the requirements of the directive 2006/42/EC on machinery of the European Parliament and of the Council. The complete EC Declaration of Conformity is available on the Internet at www.pilz.com/downloads.

Representative: Pilz GmbH & Co. KG, Felix-Wankel-Str. 2, 73760 Ostfildern, Germany

Support

Technical support is available from Pilz round the clock.

Americas

Brazil

+55 11 97569-2804

Canada

+1 888 315 7459

Mexico

+52 55 5572 1300

USA (toll-free)

+1 877-PILZUSA (745-9872)

Asia

China

+86 400-088-3566

Japan

+81 45 471-2281

South Korea

+82 31 778 3300

Australia and Oceania

Australia

+61 3 95600621

New Zealand

+64 9 6345350

Europe

Austria

+43 1 7986263-444

Belgium, Luxembourg

+32 9 3217570

France

+33 3 88104003

Germany

+49 711 3409-444

Ireland

+353 21 4804983

Italy, Malta

+39 0362 1826711

Scandinavia

+45 74436332

Spain

+34 938497433

Switzerland

+41 62 88979-32

The Netherlands

+31 347 320477

Türkiye

+90 216 5775552

United Kingdom

+44 1536 462203

**You can reach our
international hotline on:**

+49 711 3409-222

support@pilz.com

Pilz develops environmentally-friendly products using ecological materials and energy-saving technologies. Offices and production facilities are ecologically designed, environmentally-aware and energy-saving. So Pilz offers sustainability, plus the security of using energy-efficient products and environmentally-friendly solutions.



CECE®, CHRE®, CMSE®, INDUSTRIAL P®, Leansafe®, Myzel®, PAS4000®, PAScal®, PASconfig®, Pilz®, PIT®, PMCPrimo®, PMCPirotego®, PMCiendo®, PMD®, PM®, PNOZ®, Primo®, PSN®, PSN®, PSS®, PVS®, SafetyBUS p®, SafetyNET p®, THE SPIRIT OF SAFETY® are registered and protected trademarks of Pilz GmbH & Co. KG in some countries. We would point out that product features may vary from the details stated in this document, depending on the status at the time of publication and the scope of the equipment. We accept no responsibility for the validity, accuracy and entirety of the text and graphics presented in this information. Please contact our Technical Support if you have any questions.

We are represented internationally. Please refer to our homepage www.pilz.com for further details or contact our headquarters.

Headquarters: Pilz GmbH & Co. KG, Felix-Wankel-Straße 2, 73760 Ostfildern, Germany
Telephone: +49 711 3409-0, E-Mail: info@pilz.com, Internet: www.pilz.com

PILZ
THE SPIRIT OF SAFETY